

ROOM-CARD-SCANNER



The Reserva Card Scanner can be used in conjunction with Reserva Room Signs to allow greater control over room booking. This enforces the following optional rules:

- ◆ Only a meeting attendee may check in to meeting
- ◆ Only a meeting attendee may shorten, extend or end a meeting
- ◆ When booking a meeting the user is added as an attendee



Please note the Reserva Connector compatibility listed below. The Reserva Connection Manager uses Active Directory for authentication, user accounts in Active Directory must match those in the calendar system. ONELAN strongly recommend that an example card is supplied to ONELAN for validation prior to ordering.

Supported standards	
MIFARE Ultralight, MIFARE Ultralight, MIFARE Classic, MIFARE Plus, MIFARE DESFire, MIFARE DESFire EV1 4K, Ntag213 M11RF08, MIFARE Plus X2K, MIFARE Plus S2K. Call ONELAN for other card types	
System	
Frequency	13,56 MHz
Interface	Modular USB 2.0 docking point
Reading distance	Up to 4cm
Reserva connector compatibility	
NFS Rendezvous Workspace	Yes
Exchange	Yes
Office 365	Yes
G Suite	No
Google Calendar	No
Hardware Compatibility	
ROOM-7T v2, ROOM-10T-POE-LED, ROOM-15T-POE	
Mechanical	
Dimensions	68 x 55 x 24 mm
Weight	30g
Warranty	
2 year return to base warranty	

Bryants Farm, Kiln Road, Dunsden, Reading. RG4 9PB
T: +44 (0)1491 411 400 F: +44 (0)1491 579 254 E: sales@onelan.com

